

## **policer**

---

**Syntax**    `policer protocol protocolValue rate rateSize burst-size burstSize`  
`no policer protocol protocolValue`

**Release Information**    Command introduced in JUNOS Release 8.0.0.

**Description**    Configures token bucket policing to rate limit SRP module traffic flows. The **no** version disables policing for a specific protocol or for all protocols.

- Options**
- *protocolValue*—Name of the protocol
  - *rateSize*—Rate, in packets per second in the range 0–10000
  - *burstSize*—Size, in bytes, in the range 0–10000

**Mode**    Control Plane Configuration

**Related Topics**    ■    Rate-Limiting Traffic Flows

---

Published: 2009-10-08