

Removing Equipment Registrations

You can delete all equipment registrations, or you can delete a specific registration. The demonstration residential portal included with the SRC Application Library provides an example of how to use equipment registration.

To remove equipment registrations:

1. Issue the **show sae registered equipment** command to view the equipment registrations.
 2. Issue the **clear sae registered equipment** command to remove all equipment registrations.
- To remove a specific registration, use the **mac-address** option and specify the media access control (MAC) address for the registration.

```
user@host> clear sae registered equipment mac-address mac-address
```

- To specify that no confirmation is requested before the software deletes the registration entries, use the **force** option.

```
user@host> clear sae registered equipment force
```

```
user@host> clear sae registered equipment mac-address mac-address force
```

