

Changing the Location of Data in the Directory

In most cases, you use the default configuration for the location of SRC data in the directory:

- Administrator-defined configuration
data—ou = *staticConfiguration*, ou = *Configuration*, o = *Management*, o = *umc*
- Programmatically defined configuration
data—ou = *dynamicConfiguration*, ou = *Configuration*, o = *Management*, o = *umc*

You can specify the full distinguished name (DN), or a DN relative to a base DN, identified as *<base>*.

You can change the location of data in the directory at the Expert CLI editing level.

Use the following configuration statements to change the location of data for a component in the directory:

```
slot number component-name initial {  
    static-dn static-dn ;  
    dynamic-dn dynamic-dn ;  
}
```

To change the location of data in the directory:

1. From configuration mode, access the configuration statement that specifies the configuration for a component on a slot.

```
[edit]  
user@host# edit slot number nic initial
```

For example:

```
[edit]  
user@host# edit slot 0 nic initial
```

2. (Optional) Change the location of administrator-defined configuration data in the directory

```
[edit slot 0 nic initial]  
user@host# set static-dn static-dn
```

3. (Optional) Change the location of programmatically defined configuration data in the directory.

```
[edit slot 0 nic initial]  
user@host# set dynamic-dn dynamic-dn
```

