

policer

Syntax `policer protocol protocolValue rate rateSize burst-size burstSize`
`no policer protocol protocolValue`

Release Information Command introduced in JUNOS Release 8.0.0.

Description Configures token bucket policing to rate limit SRP module traffic flows. The **no** version disables policing for a specific protocol or for all protocols.

- Options**
- *protocolValue*—Name of the protocol
 - *rateSize*—Rate, in packets per second in the range 0–10000
 - *burstSize*—Size, in bytes, in the range 0–10000

Mode Control Plane Configuration

Related Topics ■ Rate-Limiting Traffic Flows

Published: 2010-01-07